

FP3/GR/TP/B

TRIPLE POLE EMERGENCY DOOR RELEASE C/W BUZZER/LED

CQR

First choice for quality

The FP3/GR/TP/B which includes a buzzer has three separate or individual change over outputs. This allows the Call Point to signal three separate devices from a single action.



- SW1/SW2 rated at 125/250v AC 12A
- SW3 rated at 125v AC 3A
- Operating voltage 12/24v DC
- Includes buzzer inside casing
- Resettable plastic operating element
- Red LED Indicator

rev. 3-10/2019

Product codes

Code	Description
FP3/GR/TP/B	FP3 Call Point with Buzzer / LED
FP3/COVER	Clear Cover for FP3 Call Point

Technical data

Operating element:	Resettable element (plastic)
Switch type:	3 x Single pole changeover
Operation voltage:	12/24 vDC
Current 12vDC:	18mA (Standby) 40mA (Operated)
Current 24vDC:	35mA (Standby) 77mA (Operated)
SW1 & SW2 contact rating:	6A
SW3 contact rating:	3A
Buzzer output:	≈80 - 60 dB(A) @ 1 m
LED indication:	GREEN (Standby), RED (Operational)
Terminal type:	2.5mm insertion type
IP Rating:	IP44 for indoor use only
Temperature range:	-10°C - +55°C
Materials:	Case ABS, Operating element PC
Size:	82 x 82 x 60mm (inc. Back Box)



www.cqr.co.uk

info@cqr.co.uk

Sales: +(0)151 606 1000 Tech: +(0)151 606 6311

CQR Security Ltd, 125 Pasture Road, Moreton, Wirral, CH46 4TH, UK

